

STANDARD MODELS

Model	Frequency Range	Output Power P_N min / typ W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power VA	Dimensions (H, D) 19"-System	Weight kg
BLMA 6080-30	6 ... 8 GHz	30 / 33	44.8 / 47 ±2	20 / 20	750	3 HU, 430 mm	22
BLMA 6080-60	6 ... 8 GHz	60 / 66	47.8 / 50 ±2	20 / 20	1000	4 HU, 630 mm	38

For individual data sheets, please click on the above model name

1 HU = 44.45 mm

STANDARD SPECIFICATIONS

Input Power:	0 dBm (1 mW) max.
Overdrive Protection:	up to +10 dBm for no damage
Input Impedance:	50 Ohm nominal
Output Impedance:	50 Ohm nominal
Input VSWR:	<2:1 typ.
Load VSWR:	infinite for no damage (100% mismatch tolerant) P_N -0.5 dB min. at VSWR 2:1
Spurious (at P_N):	-50 dBc typ. (excluding harmonics)
Class of Operation:	A-linear or AB-linear

GENERAL

RF Input:	<12 GHz	N-f, standard on rear panel
	12 bis 18 GHz	SMA-f, standard on front panel
	>18 GHz	2.92 mm-f, standard on front panel
RF Output:	<12 GHz	N-f, standard on rear panel
	12 to 18 GHz	SMA-f, standard on front panel
	>18 GHz	2.92 mm-f, standard on front panel
Mains Supply:	Line Power:	
	Line Power	
	<800 VA	100 ... 240 V AC ±10%
	800 ... 3000 VA	200 ... 240 V AC ±10%
	>3000 VA	3x 400 V AC ±10%
Elapsed Time Meter:	via status display	
Ambient Temperature:	0 ... +45 °C	
Storage Temperature:	-20 ... +85 °C	
Relative Humidity:	up to 95% (non-condensing)	
Operating Altitude:	up to 2000 m above sea level	
Vibration and Shock:	MIL-STD-810 G	
Cooling:	forced air with integral blower	
	air intake from front, air exhaust at rear	

OPTIONS

A) RF-Sample Ports *)	L) LAN Remote Control
B) External Dual Directional Coupler	N) Harmonics Filtering *)
C) IEEE-488.2 GPIB Remote Control	R) RS-232C Remote Control
D) Front Panel RF Connectors	S) Internal RF Switching Unit *)

BLMA 6 ... 8 GHz Solid State Amplifiers

E) RF Power Indication (digital) *)
F) Gain Adjustment *)
G) Output Isolator *)
H) DC Supply
I) 3x 208 V AC / 60 Hz

U) USB Remote Control
W) Liquid Cooling
X) External Control of other Amplifiers

*) These options may reduce output power and/or gain